Product details:

Item No.: 844552 Model No.: AJ220 Technical data: Input:5V/0.8A Luminous flux of night light: <60Lm Power of light: around 1W

Tools list:




- 1: Screwdriver
- 2: Utility knife
- 3: Electric screwdriver
- 4: Soldering iron

Instructions on how to remove the light source:

Step1: Remove the screws from the metal cage with screwdriver.



Step2: Pull out the lampshade by hand, exposing the lighting board.



Step3: Remove screws with electric screwdriver and open plastic cover.







Step4: Remove the wire of lighting board by hand and then remove the battery cable by soldering iron.



Step5: Remove the screws on the plastic cover of the lighting board with electric screwdriver to separate the plastic cover from lighing board.



Step6: Use utility knife to raise the wire casing and now the light source was removed without being permanently damaged for verification purposes.



Red line: Positive pole " + " Orange line: Negative pole "-"(cold light) Yellow line: Negative pole "-"(warm light)